

Fingerprint Time Attendance Terminal K40

Card Report	
Date	Time
01/01/2012	08:00
01/01/2012	08:05
01/01/2012	08:10
01/01/2012	08:15
01/01/2012	08:20
01/01/2012	08:25
01/01/2012	08:30
01/01/2012	08:35
01/01/2012	08:40
01/01/2012	08:45
01/01/2012	08:50
01/01/2012	08:55
01/01/2012	09:00
01/01/2012	09:05
01/01/2012	09:10
01/01/2012	09:15
01/01/2012	09:20
01/01/2012	09:25
01/01/2012	09:30
01/01/2012	09:35
01/01/2012	09:40
01/01/2012	09:45
01/01/2012	09:50
01/01/2012	09:55
01/01/2012	10:00



You can use Excel; you can be an excellent Workforce Management Manager!



K40 SSR Fingerprint Time Attendance Terminal

Introduction

K40 is a 2.8-inch TFT screen Time Attendance & Simple Access Control Terminal. It has interfaces for third party electric lock and exit button. TCP/IP and USB Host make data management extremely easy. Most importantly, the built-in backup battery can eliminate the trouble of power-failure. With elegant appearance and reliable quality, you can get the best from it.

eLock[®]
Your Security is Our Responsibility

Kyodensha Technologies (M) Sdn Bhd (2057536-M)
Digit Innovation Technologies (M) Sdn Bhd (646972-U)

No. 12A Jalan PPU3A,
Pusat Teknologi Sinar Puchong
47150 Puchong Selangor, Malaysia

TEL +603-8066 4636 +603-8051 5788
FAX +603-8051 4919
WEB www.elock2u.net
EMAIL enquiry@elock2u.net

Fingerprint Time Attendance Terminal K40

Features :

- TCP/IP, USB Host
- Build-in Battery
- Simple Access Control
- Multi Languages
- Report In Excel Forms



Specifications :

Model :	K40
Display :	2.8-inch TFT Screen
Software :	ZKTime 5.0
Communication :	TCP/IP, USB Host
Fingerprint Capacity :	1,000 Fingerprint
ID Card Capacity :	1,000 (Add in EM Card Module)
Records Capacity :	80,000 Records
Standard Function :	Build In Backup Battery (4 hour backup, 7.4V 2000mAH) Electric Lock, Door Sensor, Exit Button
Power Supply :	DC 12V/1.5A
Operating Temperature :	0 ~ 45°C (32 ~ 113°F)
Operating Humidity :	20 ~ 80%
Dimension (L*W*T) :	184(L) x 136(W) x 37.6(T)mm

Fingerprint Time Attendance Terminal K40

System Configuration :

